



UNCONTROLLED DOCUMENT

NAME Hayden Hall

PHONE 4941

START DATE 8/9/2004

END DATE 12/31/2004

Simplified

Programming for Standard Operations For 957 Series

Phone has been preset to Standard SMARTPHONE III Operation.

The following are all separate steps and can be done in any order that you desire.

Basic Programming 1 – 3. Advanced Programming 4 – 7.

1. Programming Telephone

- a. Press Start
- b. Press Set (key in telephone number)
- c. Press M1
- d. Press Set (key in telephone number)
- e. Press M2
- f. Press and Hold Stop for 2.5 seconds

2. Programming Call Transfer

- a. Press Start
- b. Press Start
- c. Speak Message – 18 seconds
- d. Press Stop
- e. Press Pause to review message
- f. Press and Hold Stop for 2.5 seconds

3. Programming Timer

- a. Press Start
- b. Press Set, Set
- c. Press the number of minutes you wish to talk
- d. Press Set
- e. Press and Hold Stop for 2.5 seconds

4. Change Telephone Security Code

Note: Default factory Security Code is 1111.

- a. Press Start
- b. Press Set, Set, Set
- c. Press 2
- d. Press 4 digit ID Code (your decision) Note this on label. Cannot be 0000.
- e. Press Stop
- f. Press and Hold Stop for 2.5 seconds

5. Ring – Down Telephone Line Programming

- a. Press Start
- b. Press Set, Pause, M1
- c. Press Set, M2
- d. Press Set, Set, Set
- e. Press 3
- f. Press 0
- g. Press Stop
- h. Press and Hold Stop for 2.5 seconds

6. Programming Consolidator Telephone ID Numbers

- a. Press Start
- b. Press Set, Set, Set
- c. Press i
- d. Key in the number for the elevator (i.e. 1-5)
- e. Press Stop
- f. Press and Hold Stop for 2.5 seconds

7. Consolidator Operation

Dial the SMARTPHONE III, all phones will automatically answer active.

1. Select Individual Phone

- Press * 1 (Phone #1)
- Press * 2 (Phone #2)
- Press * 3 (Phone #3)
- Press * 4 (Phone #4)
- Press * 5 (Phone #5)

2. Select All Phones Press * 0 (2 way conversation with all units)

3. Select all phones (page mode) Press * 9 (Listen mode only, in elevator)

